

Professional Tools ❖ Router



- Easy, flexible routing for up to eight stereo or mono processors
- Selection and pre-listening of up to eight stereo or mono sources
- Class A headphone amp on board
- Efficient hardware management, i. e. for selection/comparison of effects, preamps, speakers etc.
- Ideally suited for product demonstration purposes
- High-end components and circuitry throughout, all connectors balanced
- As with all SPL products, the Router is conceived, designed and hand-built in Germany

The SPL Router. Smart signal path management.



Inputs

Onboard inputs allow two sources to be connected to the Router

1. The front-panel XLR mic input with control LED allows easy comparison of channel strips, mic preamps etc. The mic signal is routed passively to external preamps—phantom power from the preamps is routed to the mic input
2. A line-level sound source (e.g. CD player) can be permanently connected to the rear-panel 1/4" TRS input connectors. The +10 dB switch raises hi-fi/consumer level to professional level

Routing selectors

Eight processors or preamps can be connected to the Router

- Any combination of stereo and mono processors/preamps is possible
- Each selector (1-8) routes the input source to the desired processor/preamplifier and the respective outputs to the headphones and line outputs
- Only one selector can be activated at a time
- Rugged high-quality mechanical switches ensure optimal audio quality
- White areas on steel front panel allow handwritten or magnetic labeling

Phones Out

Two stereo headphones can be connected to the Router

- The front-panel phones out (1/4" TRS connector) is parallel to the rear-panel output
- The volume control sets the output level of both the front and rear headphone outputs
- A mono switch with control LED allows accurate monitoring of single-channel devices (i.e. channel strips or mic preamps)
- The rear-panel phones out prevents headphones theft in demonstration racks



Phones Out/Stereo Outputs

- The rear-panel phones out (1/4" TRS connector) is parallel to the front-panel phones out. The volume is set by the volume control on the front panel. Both headphone outputs may be used simultaneously
- The stereo line-level outputs (dual 1/4" TRS connectors) deliver the output signal of the selected processor/preamplifier. The output signal is balanced when stereo plugs are inserted; mono plugs generate an unbalanced output signal

Send and Return connections

- Four D-Sub 25 connectors allow connection of up to 16 send and return channels
- The two send connectors distribute the input source to eight stereo or mono processors
- The two return connectors receive the output of eight stereo or mono processors
- All send and return connections are fully balanced

Stereo Inputs


- A balanced line-level input for a stereo source is provided on the rear panel (dual 1/4" TRS connectors)
- The input path is balanced when stereo plugs are inserted; mono plugs generate an unbalanced signal path



Applications

1. PROCESSOR/SPEAKER ROUTING (select, compare, demonstrate)

1 stereo source
(e. g. CD player)



Up to 8 processors
(via send/returns)
Up to 8 speaker pairs
(via sends)

2. PREAMPLIFIER/CHANNEL STRIP ROUTING (select, compare, demonstrate)

1 microphone



8 mic preamps/
channel strips

3. SOURCE SELECTION (CD, DAW, DAT, CDR, TAPE etc.)


8 sources
(select/compare up to 8
stereo sources)



Selected source
(output to console,
monitoring or
headphone amp)

4. COMBINED SOURCE AND PROCESSOR ROUTING (with two routers)

8 sources (via returns)



8 processors
(via send/returns)

Technical Specifications SPL Router, Model 2269

STEREO INPUTS/SEND connectors

Maximum input level:	+19 dBu
Input impedance:	10 kOhms
CCMR (1 kHz):	>70 dB
Maximum output level:	+20 dBu
THD+N (+10 dBu):	>105 dB
Noise:	-98.2 dBu
Noise (+10 dB):	-89.5 dBu
Freq. response (-0.5 dB):	10 Hz-80 kHz

STEREO OUTPUTS/RETURN connectors

Maximum input level:	+19 dBu
Input impedance:	10 kOhms
CCMR (1 kHz):	>70 dB
Maximum output level:	+19 dBu
THD+N (+10 dBu):	>100 dB
THD+N (Fixed):	>112 dB
Noise:	-98.2 dBu
Freq. response (-0.5 dB):	10 Hz-80 kHz

PHONES OUT

Output impedance:	0.2 Ohms
Maximum output voltage:	50 Ohms: 3.57 Veff 150 Ohms: 5.74 Veff 300 Ohms: 6.73 Veff 600 Ohms: 7.11 Veff
THD+N (150 Ohms, 4 Veff):	>95 dB

Power consumption: 7 W

Housing/measures: Standard EIA 19 inch housing, 1 U
44 x 480 x 112 mm (H x B x T)

Weight: 2 kg

Technical specifications subject to change without notice.

SPL Germany: Sohlweg 55, 41372 Niederkruechten

Phone: (+49) 2163 983 40, Fax: (+49) 2163 983 420
info@soundperformancelab.com/www.soundperformancelab.com

SPL USA: 2498 Rikkard Drive, Thousand Oaks, CA 91362

Phone: (+1) 805 241 5140, Fax: (+1) 805 435 7455
info@spl-usa.com/www.spl-usa.com

International Sales: ICM GmbH

Phone: (+49) 7435 910 330, Fax (+49) 7435 910 332
info@icm-consult.com/www.icm-consult.com

All you need is imagination,
good ears and three letters:

